

## 2SB1009 - 2SB988

Автор: Administrator  
09.08.2010 14:54 -

---

### Справочник, импортные транзисторы 2SB1009, 2SB988

#### 2SB1009 - 2SB988

- 2SB1009 SI-P 40V 2A 10W 100MHz
- 2SB1010 SI-P 40V 2A 0.75W 100MHz
- 2SB1012K P-DARL 120V 1.5A 8W
- 2SB1013 SI-P 20V 2A 0.7W
- 2SB1015 SI-P 60V 3A 25W 0.4us
- 2SB1016 SI-P 100V 5A 30W 5MHz
- 2SB1017 SI-P 80V 4A 25W 9MHz
- 2SB1018 SI-P 100V 7A 30W 0.4us
- 2SB1020 P-DARL+D 100V 7A 30W 0.8us
- 2SB1023 P-DARL+D 60V 3A 20W B=5K
- 2SB1035 SI-P 30V 1A 0.9W 100MHz
- 2SB1039 SI-P 100V 4A 40W 20MHz
- 2SB1050 SI-P 30V 5A 1W 120MHz
- 2SB1055 SI-P 120V 6A 70W 20MHz
- 2SB1065 SI-P 60V 3A 10W
- 2SB1066 SI-P 50V 3A 1W 70MHz
- 2SB1068 SI-P 20V 2A 0.75W 180MHz
- 2SB1071 SI-P 40V 4A 25W 150MHz
- 2SB1077 P-DARL 60V 4A 40W B>1K
- 2SB1086 SI-P 160V 1.5A 20W 50MHz
- 2SB1098 P-DARL+D 100V 5A 20W B=80
- 2SB1099 P-DARL+D 100V 8A 25W B=6K
- 2SB1100 P-DARL+D 100V 10A 30W B=6
- 2SB1109 SI-P 160V 0.1A 1.25W
- 2SB1109S SI-P 160V 0.1A 1.25W

## 2SB1009 - 2SB988

Автор: Administrator  
09.08.2010 14:54 -

---

2SB1117 SI-P 30V 3A 1W 280MHz  
2SB1120 SI-P 20V 2.5A 0.5W 250MHz  
2SB1121T SI-P 30V 2A 150MHz  
2SB1123 SI-P 60V 2A 0.5W 150MHz  
2SB1132 SI-P 40V 1A 0.5W 150MHz  
2SB1133 SI-P 60V 3A 25W 40MHz  
2SB1134 SI-P 60V 5A 25W 30W  
2SB1135 SI-P 60V 7A 30W 10MHz  
2SB1136 SI-P 60V 12A 30W 10MHz  
2SB1140 SI-P 25V 5A 10W 320MHz  
2SB1141 SI-P 20V 1.2A 10W 150MHz  
2SB1143 SI-P 60V 4A 10W 140MHz  
2SB1146 P-DARL 120V 6A 25W  
2SB1149 P-DARL 100V 3A 15W B=10K  
2SB1151 SI-P 60V 5A 20W  
2SB1154 SI-P 130V 10A 70W 30MHz  
2SB1156 SI-P 130V 20A 100W  
2SB1162 SI-P 160V 12A 120W  
2SB1163 SI-P 170V 15A 150W  
2SB1166 SI-P 60V 8A 20W 130MHz  
2SB1168 SI-P 120V 4A 20W 130MHz  
2SB1182 SI-P 40V 2A 10W 100MHz  
2SB1184 SI-P 60V 3A 15W 70MHz  
2SB1185 SI-P 50V 3A 25W 70MHz  
2SB1186 SI-P 120V 1.5A 20W 50MHz  
2SB1187 SI-P 80V 3A 35W  
2SB1188 SI-P 40V 2A 100MHz  
2SB1202 SI-P 60V 3A 15W 150MHz

## 2SB1009 - 2SB988

Автор: Administrator  
09.08.2010 14:54 -

---

2SB1203 SI-P 60V 5A 20W 130MHz  
2SB1204 SI-P 60V 8A 20W 130MHz  
2SB1205 SI-P 25V 5A 10W 320MHz  
2SB1212 SI-P 160V 1.5A 0.9W 50MHz  
2SB1223 P-DARL+D 70V 4A 20W 20MHz  
2SB1236 SI-P 120V 1.5A 1W 50MHz  
2SB1237 SI-P 40V 1A 1W 150MHz  
2SB1238 SI-P 80V 0.7A 1W 100MHz  
2SB1240 SI-P 40V 2A 1W 100MHz  
2SB1243 SI-P 60V 3A 1W  
2SB1254 P-DARL 160V 7A 70W  
2SB1255 P-DARL 160V 8A 100W B>5K  
2SB1258 P-DARL+D 100V 6A 30W B>1K  
2SB1274 SI-P 60V 3A 30W 100MHz  
2SB1282 P-DARL+D 100V 4A 25W 50MHz  
2SB1292 SI-P 80V 5A 30W  
2SB1302 SI-P 25V 5A 320MHz  
2SB1318 P-DARL+D 100V 3A 1W B>200  
2SB1326 SI-P 30V 5A 0.3W 120MHz  
2SB1329 SI-P 40V 1A 1.2W 150MHz  
2SB1330 SI-P 32V 0.7A 1.2W 100MHz  
2SB1331 SI-P 32V 2A 1.2W 100MHz  
2SB1353E SI-P 120V 1.5A 1.8W 50MHz  
2SB1361 SI-P 150V 9A 100W 15MHz  
2SB1370 SI-P 60V 3A 30W 15MHz  
2SB1373 SI-P 160V 12A 2.5W 15MHz  
2SB1375 SI-P 60V 3A 25W 9MHz  
2SB1382 P-DARL+D 120V 16A 75W B>2

## 2SB1009 - 2SB988

Автор: Administrator  
09.08.2010 14:54 -

---

2SB1393 SI-P 30V 3A 2W 30MHz  
2SB1420 SI-P 120V 16A 80W 50MHz  
2SB1425 SI-P 20V 2A 1W 90MHz  
2SB1429 SI-P 180V 15A 150W 10MHz  
2SB1434 SI-P 50V 2A 1W 110MHz  
2SB1468 SI-P 60/30V 12A 25W  
2SB1470 P-DARL 160V 8A 150W B>5K  
2SB1490 P-DARL 160V 7A 90W B>5K  
2SB1493 P-DARL 160/140V 7A 70W 20  
2SB1503 P-DARL 160V 8A 120W B>5K  
2SB1556 P-DARL 140V 8A 120W B>5K  
2SB1557 P-DARL 140V 7A 100W B>5K  
2SB1559 P-DARL 160V 8A 80W B>5K  
2SB1560 P-DARL 160V 10A 100W 50MHz  
2SB1565 SI-P 80V 3A 25W 15MHz  
2SB1587 P-DARL+D 160V 8A 70W B>5K  
2SB1624 P-DARL 110V 6A 60W B>5K  
2SB206 GE-P 80V 30A 80W  
2SB324 GE-P 32V 1A 0.25W  
2SB337 GE-P 50V 7A 30W LF-POWER  
2SB407 GE-P 30V 7A 30W  
2SB481 GE-P 32V 1A 6W 15KHz  
2SB492 GE-P 25V 2A 6W  
2SB511E SI-P 35V 1.5A 10W 8MHz  
2SB524 SI-P 60V 1.5A 10W 70MHz  
2SB527 SI-P 110V 0.8A 10W 70MHz  
2SB531 SI-P 90V 6A 50W 8MHz  
2SB536 SI-P 130V 1.5A 20W 40MHz

## 2SB1009 - 2SB988

Автор: Administrator  
09.08.2010 14:54 -

---

2SB537 SI-P 130V 1.5A 20W 60MHz  
2SB541 SI-P 110V 8A 80W 9MHz  
2SB544 SI-P 25V 1A 0.9W 180MHz  
2SB546A SI-P 200V 2A 25W 5MHz  
2SB549 SI-P 120V 0.8A 10W 80MHz  
2SB557 SI-P 120V 8A 80W  
2SB560 SI-P 100V 0.7A 0.9W 100MHz  
2SB561 SI-P 25V 0.7A 0.5W  
2SB564 SI-P 30V 1A 0.8W  
2SB598 SI-P 25V 1A 0.5W 180MHz  
2SB600 SI-P 200V 15A 200W 4MHz  
2SB601 P-DARL 100V 5A 30W  
2SB605 SI-P 60V 0.7A 0.8W 120MHz  
2SB621 SI-N 25V 1.5A 0.6W 200MHz  
2SB621A SI-N 50V 1A 0.75W 200MHz  
2SB631 SI-P 100V 1A 8W  
2SB632 SI-P 25V 2A 10W 100MHz  
2SB633 SI-P 100V 6A 40W 15MHz  
2SB637 SI-P 50V 0.1A 0.3W 200MHz  
2SB641 SI-P 30V 0.1A 120MHz  
2SB647 SI-P 120V 1A 0.9W 140MHz  
2SB649A SI-P 160V 1.5A 1W 140MHz  
2SB656 SI-P 160V 12A 125W 20MHz  
2SB673 P-DARL+D 100V 7A 40W 0.8us  
2SB676 P-DARL 100V 4A 30W 0.15us  
2SB681 SI-N 150V 12A 100W 13MHz  
2SB688 SI-P 120V 8A 80W 10MHz  
2SB700 SI-P 160V 12A 100W

**2SB1009 - 2SB988**

Автор: Administrator  
09.08.2010 14:54 -

---

**2SB703□□□□□□ SI-P 100V 4A 40W 18MHz**